



# TM-CB A S1 01210P

## PARAMETERS

IP	IP30
Dimension	S1 : 1208 x 501 x 328 mm
Power supply	230 V AC / 50 Hz
Nominal voltage	216 V DC
Batteries	Maintenance-free lead-acid batteries, service life up to 12 years
Charging	
Capacity 1 h	< 1560W   12 Ah
Capacity 2 h	< 1110 W   12 Ah
Capacity 3 h	< 650 W   12 Ah
Capacity 8 h	< 298 W   12 Ah
Maximum number of emergency fittings / circuit	20
Maximum number of circuits	10
Maximum number of stations	1
Maximum number of substations (63) + station (1)	64
Maximum number of emergency fittings in the system	12 800
	<ul style="list-style-type: none"> <li>- power supply of emergency luminaires from one point.</li> <li>- monitoring of circuits, luminaires and grounding status.</li> <li>- modular design for easy expansion.</li> <li>- touch navigation, easy to use interface.</li> <li>- correct configuration makes the system maintenance-free.</li> <li>- building visualisation using the ELVIS program.</li> </ul>
Basic version only monitoring of circuits	Only the current of the individual circuits is monitored. The system informs the user about the damage occurrence, giving the circuit number on which the failure occurred, e.g. ballast damage, fluorescent lamp burnout.
Extended version monitoring of single luminaires	each luminaire has a built-in addressable module that monitors the current. Thanks to this, the system can inform the user exactly which luminaire is a problem. Thanks to the use of addressed modules it is possible to flexibly configure the operation mode.



# SYSTEM COMPONENTS

